

### Zenith55

**GNSS** Receiver



## Smart choice for growing businesses

- Professional-grade performance with practical value in mind.
- Multi-frequency with over 600 channels for enhanced tracking and performance.
- Robust design (IP68) to safeguard your investment.

### **Productive** workflows

- Calibration-free tilt compensation for fast data collection without levelling the pole.
- Multi-constellation support for continuous, reliable data.
- Comprehensive GeoMax Support at your fingertips to maximize efficiency.

# Complete solution, optimal performance

- Fully integrated into the GeoMax ecosystem.
- Streamlined connection with X-PAD field software, robotic total stations, and field controllers.
- Complimentary field software updates to maintain peak functionality.



Scan to learn more about the **Zenith55** 







geomax-positioning.com

### Zenith55

#### Professional-grade performance, practical value

The Zenith55 is a professional-grade GNSS smart antenna that combines advanced features with practical value, all backed by exemplary GeoMax support. It offers efficient workflows that generate a strong return on investment for construction and surveying professionals.

Integrated into the GeoMax ecosystem, the Zenith55 works seamlessly with GeoMax robotic total stations, field controllers and the X-PAD field software. This makes it more than just a GNSS receiver – it's a comprehensive solution that ensures dependable precision and boosts productivity.

VARIANTS	4G LTE UHF COMPENSATION
GeoMax Zenith55 LTE-UHF-IM	
RECEIVER SPECIFICATIONS	
Measurement Engine	600+ channels, multi-frequency, multi-constellation
GPS tracking	L1 C/A, L1P, L1C, L2C, L2P, L5
GLONASS tracking	L1 C/A, L2 C/A, L3**
BeiDou tracking	B1l, B1C, B2l, B2a, B2b, B3l, ACEBOC
Galileo tracking	E1, E5a, E5b, E6, AltBOC
QZSS tracking	L1 C/A, L1C, L2C, L5, L6
NavIC	L5
SBAS (EGNOS, WAAS, MSAS, GAGAN)	L1, L5
Positioning rate	10 Hz
Time for Initialisation	Typically 6s
QUALITY MODE	
Tilt Compensation	Calibration-free, Resistant to magnetic interferences
COMMUNICATION	
4G LTE module	QUECTEL EG25-G LTE FDD, LTE TDD, UMTS, GSM
RTK data protocols	RTCM 2.1, 2.3, 3.0, 3.1, 3.2, 3.3, 3.4, CMR, CMR+
NMEA Output	NMEA v3.1, NMEA v4.1
UHF radio module	TRM101, 500 mW, 1000 mW transceiver, 410-470 MHz
Bluetooth®	2.1 +EDR, V5.0 QR-iConnect functionality
WLAN	802.11 b/g/n Hotspot / client mode
TNC connector	UHF antenna
Communication port	USB, serial & power

RECEIVER ACCURAC	Y & PERFORMANCE *
RTK	Hz: 10 mm + 1 ppm (rms) V: 20 mm + 1 ppm (rms)
Network RTK	Hz: 10 mm + 0.5 ppm (rms) V: 20 mm + 0.5 ppm (rms)
Static	Hz: 5 mm + 0.5 ppm (rms) V: 8 mm + 0.5 ppm (rms)
Tilt compensated real-time kinematic	Additional Hz uncertainty 2 cm up to 30° tilt
INTERFACES	
Keyboard	On/Off button
LED status indicators	Position, RTK, Power, Bluetooth®
Data recording	Dual; microSD card and 8 GB internal memory
LTE/TCP/IP	Removable SIM card
POWER SUPPLY	
Two internal batteries	Hot-swappable, Li-Ion 3.4 Ah / 7.2 V
Operating time	12.5 h in static / 11 h in rover mode
External power	9 V to 28 V, LEMO® plug
PHYSICAL SPECIFICATIONS	
Dimensions	Height 75 mm, ø 166.8 mm
Weight	1.14 kg without batteries
Operating temp.	-40°C to 65°C
Environmental protection	IP68 (IEC 60529) Withstands powerful jets and temp. immersion under water MIL-STD-810G 1 506.6 & 1 512.6 Fully dust tight MIL-STD-810G 1 510.6
Humidity	MIL-STD-810H 1 507.6
Vibration	Mechanical stress resistant according to ISO 9022-36-05
Shock	Withstands 2 m drop onto hard surface

<sup>\*</sup> Measurement accuracy and reliability are dependent on various factors including satellite geometry, obstructions, observation time, ionospheric conditions, multipath, etc.

Figures quoted assume normal to favourable conditions. GeoMax reserves the right to change, without notice, product offerings or specifications.



#### Copyright Hexagon AB.

Illustrations, descriptions and technical specifications are not binding and may change. All trademarks and trade names are those of their respective owners.

<sup>\*\*</sup> Glonass L3 will be provided through future firmware upgrade.